# FSP Champ Tower 3K gruppo di continuità (UPS) Doppia conversione (online) 3 kVA 2700 W



**Marchio :** FSP

**Codice prodotto:** PPF24A1807

**Nome del prodotto :** Champ Tower 3K

FSP Champ Tower 3K. Topologia UPS: Doppia conversione (online), Potenza in uscita: 3 kVA, Potenza in uscita: 2700 W. Tipo di uscita AC: Accoppiatore C13, Tipo di porta USB: USB di tipo B, Tipo interfaccia seriale: RS-232. Capacità della batteria: 9 Ah, Voltaggio della batteria: 12 V, Tempo di salvataggio minimo a pieno carico: 3,5 min. Fattore di forma: Tower, Colore del prodotto: Nero, Tipo di controllo: Pulsanti. Cavi inclusi: Cavo di alimentazione di ingresso, Cavo USB



| Caratteristiche | |
|---|---|
| Topologia UPS * | Doppia conversione (online) |
| Potenza in uscita * | 3 kVA |
| Potenza in uscita * | 2700 W |
| Forma d'onda * | Sinusoidale |
| Tensione operativa in entrata (min) * | 120 V |
| Tensione operativa in entrata (max) * | 300 V |
| Frequenza di ingresso * | 40 - 70 Hz |
| Tensione operativa di uscita (min) | 200 V |
| Tensione di uscita (max) | 240 V |
| frequenza output | 47/63 Hz |
| Regolazione della tensione di uscita | 1% |
| Tempo di risposta | 0 ms |
| Fattore di potenza | 0,99 |
| Fattore di cresta | 3:1 |
| Distorsione armonica totale (THD) (carico lineare) | 3% |
| Distorsione armonica totale (THD) (carico non lineare) | 6% |
| Emissione acustica | 50 dB |
| Allarmi sonori | ✔ |
| Modalità allarme acustici | Allarme in funzionamento a batteria, Guasto, Allarme per batteria scarsa, Allarme di sovraccarico |

| Connettività | |
|---|---|
| Tipo di uscita AC | Accoppiatore C13 |
| Numero di jumpers uscita IEC | 4 |
| Porta USB | ✔ |
| Quantità porte USB 2.0 | 1 |
| Tipo di porta USB | USB di tipo B |
| Interfaccia seriale | ✔ |
| Tipo interfaccia seriale | RS-232 |

| Batteria | |
|---|---|
| Capacità della batteria | 9 Ah |
| Voltaggio della batteria | 12 V |
| Numero di celle della batteria | 6 |
| Tempo di salvataggio minimo a pieno carico | 3,5 min |
| Tempo di salvataggio minimo a mezzo carico | 9,8 min |
| Tempo di ricarica della batteria (90%) | 4 h |

| Design | |
|---|---|
| Fattore di forma * | Tower |
| Colore del prodotto * | Nero |
| Tipo di controllo | Pulsanti |
| Tipo di display | LCD |
| Indicatori LED | ✔ |

| Condizioni ambientali | |
|---|---|
| Intervallo temperatura di funzionamento | 0 - 40 °C |
| Range di umidità di funzionamento | 20 - 90% |

| Contenuto dell'imballo | |
|---|---|
| Batterie incluse | ✔ |
| Cavi inclusi | Cavo di alimentazione di ingresso, Cavo USB |
| Manuale dell'utente | ✔ |

| Dimensioni e peso | |
|---|---|
| Larghezza | 190 mm |
| Profondità | 421 mm |
| Altezza | 318 mm |
| Peso | 27,6 kg |

| Dati su imballaggio | |
|---|---|
| CD software | ✔ |

| Connettività | | Dati logistici | |
|---|---|---|---|
| Porta RS-232 | 1 | Codice del Sistema Armonizzato (SA) | 85078000 |

4711140487618

2000000852225

**Catalog Object Cloud**

Disclaimer. The information published here (the "Information") is based on sources that can be considered reliable, typically the manufacturer, but this Information is provided "AS IS" and without guarantee of correctness or completeness. The Information is only indicative and can be changed at any time without notification. No rights can be based on the Information. Suppliers or aggregators of this Information do not accept any liability with regard to the content of (web)pages and other documents, including its Information. The publisher of the Information can not be held liable for the content of 3rd party websites that are linking this Information or are linked to from this Information. You as the User of the Information are solely responsible for the choice and usage of this Information. You are not entitled to transfer, copy or otherwise multiply or distribute the Information. You are obliged to follow the directions of the copyright owner(s) with regard to the use of the Information. Exclusively Dutch law is applicable. With regard to price and stock data on the site, the publisher followed a number of starting points, which are not necessarily relevant for your private or business circumstances. Therefore, the price and stock data are only indicative and are subject to changes. You are personally responsible for the way you use and apply this information. As a user of the Information or sites or documents in which this Information is included, you will adhere to standard fair use including avoidance of spamming, ripping, intellectual-property violations, privacy violations, and any other illegal activity. Automated scraping, data mining, or harvesting for the purpose of training machine learning models, neural networks, or artificial intelligence systems is strictly prohibited without a commercial license.

Publication date: 17-NOV-2026. Prints or copies of Information are only valid on the printed Publication date